Dimming Compatibility Matrix with 120 Vac TRIAC and ELV Dimmers

EBR010U-0200-42		Total Score:	97.5%	Driver Current (mA) with no Dimmer:		200	Driver Light (FC) with no Dimmer:			Scoring: 0 - Needs improvement; 1 - Unlikely to be noticed; 2 - No issues				
		Average Min. Dimming:	4.0%											
Dimmer List		Indiv. Score	Light Output (Foot Candle)		Current (mA)		Dimming Range[1]		Smooth Dimming[2]	Sag[3]	No Start Flash[4]	Flicker[5]	Shimmer[6]	Able to turn off[7]	Audible Noise[8]
Mfg.	Model	%	Max	Min	Max	Min	Max5	Min6		%					
Lutron	S-603PG	91.7%			175	10	88%	5%	2	13.0%	2	2	2	2	2
Leviton	IPI06-1LZ	100.0%			199	1	100%	1%	2	1.0%	2	2	2	2	2
Leviton	6631-2	100.0%			199	1	100%	1%	2	1.0%	2	2	2	2	2
Lutron	DVCL-153P	83.3%			199	1	100%	1%	2	1.0%	2	2	0	2	2
Lutron	DV600P	100.0%			198	9	99%	5%	2	1.0%	2	2	2	2	2
Lutron	TGCL-153P	100.0%			199	4	100%	2%	2	1.0%	2	2	2	2	2
Lutron	S600P	100.0%			199	4	100%	2%	2	1.0%	2	2	2	2	2
Leviton	VPE06	95.8%			199	11	100%	6%	2	1.0%	1	2	2	2	2
Lutron	DVELV303P	100.0%			198	5	99%	3%	2	1.0%	2	2	2	2	2
Lutron	SELV300P	100.0%			196	6	98%	3%	2	2.0%	2	2	2	2	2
Leviton	6673-10W				199	16	100%	8%	2	1.0%	2	2	2	2	2
Leviton	6683-IW	95.8%			200	2	100%	1%	2	0.0%	1	2	2	2	2
Leviton	6161	91.7%			199	25	100%	13%	2	1.0%	2	2	2	1	2
Leviton	6633-P	95.8%			200	1	100%	1%	2	0.0%	1	2	2	2	2
Lutron	TG-600P	100.0%			198	18	99%	9%	2	1.0%	2	2	2	2	2
Cooper	DLC03P	95.8%			199	1	100%	1%	2	1.0%	1	2	2	2	2
Lutron	LG600P	100.0%			198	4	99%	2%	2	1.0%	2	2	2	2	2
Lutron	DV603P														2
Cooper	SLC03P	95.8%			199	1	100%	1%	2	1.0%	1	2	2	2	2
Leviton	IPE04	100.0%			199	7	100%	4%	2	1.0%	2	2	2	2	2
Lutron	MAELV600	100.0%			198	14	99%	7%	2	1.0%	2	2	2	2	2
Lutron	FAELV500	100.0%			199	16	100%	8%	2	1.0%	2	2	2	2	2
Lightolier	ZP260QEW	100.0%			199	7	100%	4%	2	1.0%	2	2	2	2	2
Cooper	DAL06P	95.8%			199	1	100%	1%	2	1.0%	1	2	2	2	2

NOTES:

1. If light is measured, then the dimming range is based on light output. If light is not measured, then the dimming range is based on the percentage of output current.
2. While adjusting the dimming level, a smooth dimming, with no sudden jumps in light output, results in a score of 2. A small jump that is only noticeable if directly staring at the light results in a score of 1.
   A large obvious jump results in a score of 0.
3. Percentage away from 100% output current when dimmer is inserted in the circuit, at the dimmer's maximum conduction angle.
4. No flash at startup (at maximum conduction angle) results in a score of 2. A smooth, but still noticeable transition from overshoot results in a score of 1. A transition with overshoot and undershoot results in a score of 0.
5. Highly visible repeating light fluctuations. No flicker results in a score of 2. Flicker results in a score of 0. There is no "1" score.
   Flicker is measured using a stable AC source delivered by a power supply. AC line voltage instability will cause visible light fluctuations.
6. Low frequency or random variations in light output that are typically less noticeable than flicker (the light output does not turn off at any point).
   No shimmer, perfect light output, results in a score of 2. Only noticeable shimmer, if staring directly at the LEDs, results in a score of 1. Obvious shimmer, even if looking away from the LEDs, results in a score of 0.
   Like Flicker, Shimmer is measured using a stable AC source delivered by a power supply. AC line voltage instability will cause visible light fluctuations.