ERP POWER

Dimming Compatibility Matrix with 120 Vac TRIAC and ELV Dimmers

EBR020U-0700-30		Total Score:	95.8%	Driver Current (mA) with no Dimmer:		698	Driver Light (FC) with no Dimmer:			Scoring: 0 - Needs improvement; 1 - Unlikely to be noticed; 2 - No issues				
		Average Min. Dimming:	6.0%											
Dimmer List		Indiv. Score	Light Output (Foot Candle)		Current (mA)		Dimming Range[1]		Smooth Dimming[2]	Sag[3]	No Start Flash[4]	Flicker[5]	Shimmer[6]	Able to turn off[7]	Audible Noise[8]
Mfg.	Model	%	Max	Min	Max	Min	Max	Min		%					
Lutron	S-603PG	91.7%			593	56	85%	8%	2	15.0%	2	2	2	2	2
Leviton	IPI06-1LZ	91.7%			694	6	99%	1%	2	1.0%	2	1	2	2	2
Leviton	6631-LW	100.0%			693	2	99%	0%	2	1.0%	2	2	2	2	2
Lutron	DVCL-153P	91.7%			692	4	99%	1%	0	1.0%	2	2	2	2	2
Lutron	DV600P	75.0%			693	49	99%	7%	0	1.0%	2	0	2	2	2
Lutron	TGCL-153P	91.7%			693	36	99%	5%	0	1.0%	2	2	2	2	2
Lutron	S600P	100.0%			694	37	99%	5%	2	1.0%	2	2	2	2	2
Leviton	VPE06	91.7%			666	61	95%	9%	2	5.0%	2	2	2	2	2
Lutron	DVELV303P	91.7%			659	44	94%	6%	2	6.0%	2	2	2	2	2
Lutron	SELV300P	100.0%			695	47	100%	7%	2	0.0%	2	2	2	2	2
Leviton	6683-IW	87.5%			693	33	99%	5%	2	1.0%	1	1	2	2	2
Leviton	6161	100.0%			694	87	99%	12%	2	1.0%	2	2	2	2	2
Leviton	6633-P	100.0%			692	16	99%	2%	2	1.0%	2	2	2	2	2
Lutron	TG-600P	100.0%			694	107	99%	15%	2	1.0%	2	2	2	2	2
Cooper	DLC03P	100.0%			692	15	99%	2%	2	1.0%	2	2	2	2	2
Lutron	LG600P	100.0%			694	59	99%	8%	2	1.0%	2	2	2	2	2
Lutron	CT103P	100.0%			692	68	99%	10%	2	1.0%	2	2	2	2	2
Cooper	SLC03P	100.0%			692	6	99%	1%	2	1.0%	2	2	2	2	2
Leviton	IPE04	100.0%			694	41	99%	6%	2	1.0%	2	2	2	2	2
Lutron	MAELV600	100.0%			693	77	99%	11%	2	1.0%	2	2	2	2	2
Lutron	FAELV500	100.0%			693	80	99%	11%	2	1.0%	2	2	2	2	2
Lightolier	ZP260QEW	100.0%			684	32	98%	5%	2	2.0%	2	2	2	2	2
Cooper	DAL06P	91.7%			693	3	99%	0%	0	1.0%	2	2	2	2	2

NOTES:

1. If light is measured, then the dimming range is based on light output. If light is not measured, then the dimming range is based on the percentage of output current.
2. While adjusting the dimming level, a smooth dimming, with no sudden jumps in light output, results in a score of 2. A small jump that is only noticeable if directly staring at the light results in a score of 1.
   A large obvious jump results in a score of 0.
3. Percentage away from 100% output current when dimmer is inserted in the circuit, at the dimmer's maximum conduction angle.
4. No flash at startup (at maximum conduction angle) results in a score of 2. A smooth, but still noticeable transition from overshoot results in a score of 1. A transition with overshoot and undershoot results in a score of 0.
5. Highly visible repeating light fluctuations. No flicker results in a score of 2. Flicker results in a score of 0. There is no "1" score.
   Flicker is measured using a stable AC source delivered by a power supply. AC line voltage instability will cause visible light fluctuations.
6. Low frequency or random variations in light output that are typically less noticeable than flicker (the light output does not turn off at any point).
   No shimmer, perfect light output, results in a score of 2. Only noticeable shimmer, if staring directly at the LEDs, results in a score of 1. Obvious shimmer, even if looking away from the LEDs, results in a score of 0.
   Like Flicker, Shimmer is measured using a stable AC source delivered by a power supply. AC line voltage instability will cause visible light fluctuations.
7. No light output when dimmer switch or button is turned off.
8. Audible noise with driver located at 3 feet and measured at 90 degree conduction angle (worst case). A strongly apparent noise resuts in a score of 0.
   A score of 1 is assigned if the noise is not very obvious, and most likely to not be noticed inside of a fixture.
9. All the dimmers are set to the widest dimming range, when the trim potentiometer is available. Testing is done with 1 dimmer per LED driver.