ERP POWER

Dimming Compatibility Matrix with 120 Vac TRIAC, ELV and 0-10 V Dimmers

ESM020W-1000-14		Total Score:	98.9%		Driver Current (mA) with no Dimmer:	995	Driver Light (FC) with no Dimmer:	803			Scoring: 0 - Needs improvement; 1 - Unlikely to be noticed; 2 - No issues			
		Avg. Min. Dimming:	6.4%											
Dimmer List		Indiv. Score	Light Output (Foot Candle)		Current (mA)		Dimming Range[1]		Smooth Dimming[2]	Sag[3]	No Start Flash[4]	Flicker[5]	Shimmer[6]	Able to turn off[7]	Audible Noise[8]
Mfg.	Model	%	Max	Min	Max	Min	Max	Min		%					
Lutron	S-603PG	100.0%	770	14	942	14	96%	2%	2	5.0%	2	2	2	2	2
Leviton	IPI06-1LZ	100.0%	803	14	995	14	100%	2%	2	0.0%	2	2	2	2	2
Leviton	6631-2	100.0%	802	4	995	3	100%	0%	2	0.0%	2	2	2	2	2
Lutron	DVCL-153P	100.0%	803	13	995	13	100%	2%	2	0.0%	2	2	2	2	2
Lutron	DV600P	100.0%	803	28	995	27	100%	3%	2	0.0%	2	2	2	2	2
Lutron	TGCL-153P	100.0%	803	59	995	56	100%	7%	2	0.0%	2	2	2	2	2
Lutron	S600P	100.0%	803	3	995	3	100%	0%	2	0.0%	2	2	2	2	2
Leviton	VPE06	95.8%	803	95	995	91	100%	12%	2	0.0%	2	2	2	2	2
Lutron	DVELV303P	100.0%	803	66	995	63	100%	8%	2	0.0%	2	2	2	2	2
Lutron	SELV300P	100.0%	803	70	995	66	100%	9%	2	0.0%	2	2	2	2	2
Leviton	6683-IW	100.0%	803	47	995	45	100%	6%	2	0.0%	2	2	2	2	2
Leviton	6161	91.7%	803	138	995	134	100%	17%	2	0.0%	2	2	2	2	2
Leviton	6633-P	100.0%	803	1	995	1	100%	0%	2	0.0%	2	2	2	2	2
Lutron	TG-600P	95.8%	803	105	995	100	100%	13%	2	0.0%	2	2	2	2	2
Cooper	DLC03P	100.0%	803	31	955	30	100%	4%	2	4.0%	2	2	2	2	2
Lutron	LG600P	100.0%	803	28	995	27	100%	3%	2	0.0%	2	2	2	2	2
Lutron	CT103P	100.0%	803	56	995	52	100%	7%	2	0.0%	2	2	2	2	2
Cooper	SLC03P	100.0%	803	10	995	10	100%	1%	2	0.0%	2	2	2	2	2
Leviton	IPE04	100.0%	803	62	995	58	100%	8%	2	0.0%	2	2	2	2	2
Lutron	MAELV600	95.8%	803	115	995	109	100%	14%	2	0.0%	2	2	2	2	2
Lutron	FAELV500	95.8%	803	117	995	112	100%	15%	2	0.0%	2	2	2	2	2
Lightolier	ZP260QEW	100.0%	803	75	995	70	100%	9%	2	0.0%	2	2	2	2	2
Cooper	DAL06P	100.0%	803	1	995	1	100%	0%	2	0.0%	2	2	2	2	2

NOTES:

1. If light is measured, then the dimming range is based on light output. If light is not measured, then the dimming range is based on the percentage of output current.
2. While adjusting the dimming level, a smooth dimming, with no sudden jumps in light output, results in a score of 2. A small jump that is only noticeable if directly staring at the light results in a score of 1.
   A large obvious jump results in a score of 0.
3. Percentage away from 100% output current when dimmer is inserted in the circuit, at the dimmer's maximum conduction angle.
4. No flash at startup (at maximum conduction angle) results in a score of 2. A smooth, but still noticeable transition from overshoot results in a score of 1. A transition with overshoot and undershoot results in a score of 0.
5. Highly visible repeating light fluctuations. No flicker results in a score of 2. Flicker results in a score of 0. There is no "1" score.
   Flicker is measured using a stable AC source delivered by a power supply. AC line voltage instability will cause visible light fluctuations.
6. Low frequency or random variations in light output that are typically less noticeable than flicker (the light output does not turn off at any point).
   No shimmer, perfect light output, results in a score of 2. Only noticeable shimmer, if staring directly at the LEDs, results in a score of 1. Obvious shimmer, even if looking away from the LEDs, results in a score of 0.
   Like Flicker, Shimmer is measured using a stable AC source delivered by a power supply. AC line voltage instability will cause visible light fluctuations.
7. No light output when dimmer switch or button is turned off.
8. Audible noise with driver located at 3 feet and measured at 90 degree conduction angle (worst case). A strongly apparent noise resuts in a score of 0.
   A score of 1 is assigned if the noise is not very obvious, and most likely to not be noticed inside of a fixture.
9. All the dimmers are set to the widest dimming range, when the trim potentiometer is available. Testing is done with 1 dimmer per LED driver.