ERP POWER

Dimming Compatibility Matrix with 120 Vac TRIAC, ELV and 0-10 V Dimmers

ESM050W-0950-50-ABL6		Total Score:	91.1%		Driver Current (mA) with no Dimmer:	941	Driver Light (FC) with no Dimmer:	4810			Scoring			
		Avg. Min. Dimming:	5.6%								0 - Needs improvement			
											1 - Unlikely to be noticed			
											2 - No issues			
Dimmer List		Indiv. Score	Light Output (Foot Candle)		Current (mA)		Dimming Range[1]		Smooth Dimming[2]	Sag[3]	No Start Flash[4]	Flicker[5]	Shimmer[6]	Able to turn off[7]	Audible Noise[8]
Mfg.	Model	%	Max	Min	Max	Min	Max	Min		%					
Lutron	S-603PG	91.7%	4370	200	845	36	91%	4%	2	10.0%	2	2	2	2	1
Leviton	IPI06-1LZ	91.7%	4810	0	941	0	100%	0%	2	0.0%	2	2	2	2	1
Leviton	6631-2	91.7%	4810	0	941	0	100%	3%	2	0.0%	2	2	2	2	1
Lutron	DVCL-153P	91.7%	4810	130	941	25	100%	3%	2	0.0%	2	2	2	2	1
Lutron	DV600P	91.7%	4810	250	941	44	100%	5%	2	0.0%	2	2	2	2	1
Lutron	TGCL-153P	91.7%	4810	250	941	46	100%	5%	2	0.0%	2	2	2	2	1
Lutron	S600P	91.7%	4810	90	941	18	100%	2%	2	0.0%	2	2	2	2	1
Leviton	VPE06	100.0%	4810	460	941	81	100%	10%	2	0.0%	2	2	2	2	2
Lutron	DVELV303P	100.0%	4810	340	941	60	100%	7%	2	0.0%	2	2	2	2	2
Lutron	SELV300P	100.0%	4810	360	941	63	100%	7%	2	0.0%	2	2	2	2	2
Leviton	6683-IW	87.5%	4810	0	941	0	100%	0%	2	0.0%	1	2	2	2	1
Leviton	6161	87.5%	4810	710	941	123	100%	15%	2	0.0%	2	2	2	2	1
Leviton	6633-P	91.7%	4810	60	941	13	100%	1%	2	0.0%	2	2	2	2	1
Lutron	TG-600P	87.5%	4810	530	941	93	100%	11%	2	0.0%	2	2	2	2	1
Cooper	DLC03P	83.3%	4810	100	941	20	100%	2%	2	0.0%	2	2	1	2	1
Lutron	LG600P	91.7%	4810	240	941	43	100%	5%	2	0.0%	2	2	2	2	1
Lutron	CT103P	91.7%	4810	390	941	69	100%	8%	2	0.0%	2	2	2	2	1
Cooper	SLC03P	83.3%	4810	40	941	10	100%	1%	1	0.0%	2	2	2	2	1
Leviton	IPE04	91.7%	4810	310	941	55	100%	6%	1	0.0%	2	2	2	2	2
Lutron	MAELV600	95.8%	4810	560	941	97	100%	12%	2	0.0%	2	2	2	2	2
Lutron	FAELV500	95.8%	4810	560	941	97	100%	12%	2	0.0%	2	2	2	2	2
Lightolier	ZP260QEW	100.0%	4810	380	941	67	100%	8%	2	0.0%	2	2	2	2	2
Cooper	DAL06P	66.7%	4810	0	941	0	100%	0%	1	0.0%	2	2	0	2	1

NOTES:

1. If light is measured, then the dimming range is based on light output. If light is not measured, then the dimming range is based on the percentage of output current.
2. While adjusting the dimming level, a smooth dimming, with no sudden jumps in light output, results in a score of 2. A small jump that is only noticeable if directly staring at the light results in a score of 1.
   A large obvious jump results in a score of 0.
3. Percentage away from 100% output current when dimmer is inserted in the circuit, at the dimmer's maximum conduction angle.
4. No flash at startup (at maximum conduction angle) results in a score of 2. A smooth, but still noticeable transition from overshoot results in a score of 1. A transition with overshoot and undershoot results in a score of 0.
5. Highly visible repeating light fluctuations. No flicker results in a score of 2. Flicker results in a score of 0. There is no "1" score.
   Flicker is measured using a stable AC source delivered by a power supply. AC line voltage instability will cause visible light fluctuations.
6. Low frequency or random variations in light output that are typically less noticeable than flicker (the light output does not turn off at any point).
   No shimmer, perfect light output, results in a score of 2. Only noticeable shimmer, if staring directly at the LEDs, results in a score of 1. Obvious shimmer, even if looking away from the LEDs, results in a score of 0.
   Like Flicker, Shimmer is measured using a stable AC source delivered by a power supply. AC line voltage instability will cause visible light fluctuations.
7. No light output when dimmer switch or button is turned off.
8. Audible noise with driver located at 3 feet and measured at 90 degree conduction angle (worst case). A strongly apparent noise resuts in a score of 0.
   A score of 1 is assigned if the noise is not very obvious, and most likely to not be noticed inside of a fixture.
9. All the dimmers are set to the widest dimming range, when the trim potentiometer is available. Testing is done with 1 dimmer per LED driver.